

8-41 good

10 from 74

## **RUNNING THE NEVCO SCOREBOARD**

**Remember, you are an "off-ice official" as the scoreboard operator.**

**See YouTube video:** <http://www.youtube.com/watch?v=QG15OBt1SaI>

- 1) Step One. Turn on (upper right hand side).
- 2) Step Two. You will be asked "Do you want to start where you left off?" ALWAYS ANSWER [NO]
- 3) Step Three. You will be asked for the Model #. ENTER THE MODEL # (from the unit).
- 4) Step Four. <sup>WIRELESS - YES</sup> You will be asked "Do you want to use the shot clock?" ALWAYS ANSWER [NO]
- 5) Step Five. You will be asked "Do you want to use penalty time out?" Answer is [YES]
- 6) Step Six. To set the time for the periods. [SET], [TIME], [1], [2], [:] (colon), [0], [0], [YES]
- 7) Step Seven. Set the period. [1]
- 8) Step Eight. Start clock when the referee drops the puck. Stop clock when the referee blows the whistle.

## **ADDING GOALS**

- 1) Press [HOME SCORE]. Screen will show "+". Press [1] to add one to the home score.
- 2) Press [GUEST SCORE]. Screen will show "+". Press [1] to add one to the guest score.

OR

- 3) Press [SET], [HOME SCORE] [#] and/or [SET], [GUEST SCORE] [#]

## **SHOTS ON GOAL**

- 1) Press [SET], [HOME SHOTS] [##] and/or [SET], [GUEST SHOTS] [##].

## **PENALTIES**

1:30

- 1) Press [SET], [HOME PENALTY]. Enter duration of penalty [1], [:] (colon), [0], [0], [YES]. Screen will show "Player". Enter player number as two digit number, [#], [#], [YES].
- 2) Press [SET], [GUEST PENALTY]. Enter duration of penalty [1], [:] (colon), [0], [0], [YES]. Screen will show "Player". Enter player number as two digit number, [#], [#], [YES].

### **CLEARING PENALTIES**

- 1) Press [HOME PENALTY], [PENALTY CLEAR], [YES]

OR

- 2) Press [GUEST PENALTY], [PENALTY CLEAR], [YES]

### **1 MINUTE BETWEEN PERIODS**

- 1) IF YOU HAVE A CURRENT PENALTY, then press [PENALTY ON/OFF]. Else, skip to step 2.
- 2) Press [SET], [TIME], [1], [:] (colon), [0], [0], [YES] and turn clock on.

### **NEW PERIOD**

- 1) IF YOU HAVE A CURRENT PENALTY, then press [PENALTY ON/OFF]. Else, skip to step 2.
- 2) Press [SET], [TIME], [1], [2], [:] (colon), [0], [0], [YES]
- 3) The screen will read "Period." Press [2] or [3].

## Scoreboard:

### How to Turn on Clock

Turn Controller On.

When asked, input model code 871.

Do you want to start where you left off? No

Do you want to operate wirelessly? Yes

Select Group, Both Scoreboards? Yes

Use Penalty Time? No

Press “set” then press “chronometer”

Do you have an auxiliary time display connected? Yes

Do you want to display chronometer time on auxiliary display? Yes

Enable chronometer key to display chronometer time on scoreboard? Yes

Set Chronometer? No

Then control off but leave the chronometer time displayed? No

*time:* **Set Time** time  
1 2 **Yes** period  
1

*horn:* after 2 seconds, switch **Time-Off** on hand-held switch

*score increment:*

**HomeScore 1 Yes**

**GuestScore 1 Yes**

*score set:*

**Set HomeScore** score  
3 **Yes**

**Set GuestScore** 3 **Yes**

*And  
Goal*

*penalty add:*

**Set HomePenalty** time  
0 2 **Yes** player:  
2 digits  
0 9

**Set GuestPenalty** 0 2 **Yes** 0 9

*penalty clear:*

use **HomePenalty** or **GuestPenalty** to select, then  
**PenaltyClear Yes**